

Wärtsilä JOVYLINE DINrail

PRODUCT LEAFLET



Our new DIN rail UPS system Wärtsilä JOVYLINE DINrail is available with an output power of 500 VA. The extremely compact system offers reliability and safeness in a very small space. The system operates energy-saving and nearly silent as it do not require any fan. The UPS offers a wide range of applications in the industrial sector, home and small office areas, as well as in measuring or relay stations. The system can also be commissioned via remote control.

EFFICIENCY AND SAFETY

The new Wärtsilä JOVYLINE DINRail UPS systems are an economical alternative to online UPS systems. The systems convince both by low operating costs and high efficiency. Due to their high reliability and low maintenance requirements, cost-intensive service hours are no longer required.

COMPACT DIN RAIL UPS SYSTEM OPTIMUM FOR USE IN INDUSTRIAL AREAS

The Wärtsilä JOVYLINE DINrail UPS systems are extremely robust and can withstand ambient temperatures of up to 50 ° C. Their reliable technology guarantees smoothly operation and fast assembly - even in small control cabinets. The UPS systems can easily be snapped onto DIN rail systems and can easily be installed in control cabinets due to their low depth. They protect connected consumers and components e.g. industrial PCs reliable from data loss by switching to battery supply without interruption, as soon as the voltage or frequency of the input network is outside the tolerance range. Wärtsilä JOVYLINE DINrail UPS systems provide an extraordinarily long bridging period; Depending on the load, the connected consumers can be supplied for up to. 1 hour (approx.) by the integrated battery. All operating and connecting elements are located on the front side and are easily accessible.

VARIETY OF APPLICATIONS

The DIN rail technology offers a wide range of industrial applications with installation in control cabinets as well as wall mounted systems. Wärtsilä JOVYLINE DINrail systems

are, however, also ideally suited for the supply of DSL routers and NAS systems in home or small office areas. Starting the UPS systems is also possible without a supply network: via a remote interface, the system can be switched on or off by remote control and can thus also be used in unmanned measuring or relay stations.

RELIABLE TECHNOLOGY

All Wärtsilä JOVYLINE DINrail UPS systems are subjected to a 48-hour "burn-in test" before delivery and tested in our in-house test field. Should there be any disturbances, we guarantee an exchange within 24 hours (within Germany).



WÄRTSILÄ JOVYLINE DINrail

TECHNICAL DATA

Power 500 VA / 400 W Input voltage 230 V \pm 20 %

Output voltage 230 V \pm 5 %

Output frequency $50 \text{ Hz} / 60 \text{ Hz} \pm 0.3 \text{ Hz}$ (at battery operation)

Battery sealed lead acid battery, maintenance-free

Switch-over time 6-10 ms

Overload capacity 105% for 20 seconds 120% for 10 seconds

130% for 3 seconds

Typical

autonomy times

 for 50 VA
 50 min

 for 100 VA
 31 min

 for 150 VA
 22 min

 for 200 VA
 15 min

 for 300 VA
 10 min

 for 400 VA
 6 min

 for 500 VA
 4 min

Dimensions 281 mm x 116 mm x 124 mm

Weight 4.4 kg
Protection class IP 20

Classification VFD-Y-311 acc. to IEC/DIN/EN 62040-3

Ambient temparature

 $\begin{array}{ccc} \text{for operation} & & \text{0 C up to } 50^{\circ} \text{ C} \\ \text{for storage} & & \text{-15}^{\circ} \text{ C up to } 60^{\circ} \text{ C} \end{array}$

Noise level <40 dB(A)

Humidity 0 - 95 %, no condensation

Positioning up to 1500 m > NN without any power decrease

Mounting DIN RAIL-adapter backsides

Scope of delivery UPS System with battery (built-in), sonitoring / shutdown software,

RS232 line, telephone cable, manual

VFD UPS SYSTEM

"Voltage and Frequency Dependent" according to IEC 62040-3 Safe and reliable protection against mains faults, voltage peaks or drops

— RAIL MOUNTING AND WALL MOUNTING POSSIBLE

— NEARLY SOUNDLESS

VERY ROBUST

ideally suited for industrial use, even for extreme ambient conditions

HIGHEST POWER WITH
LOWEST SPACE
REQUIREMENTS

— REMOTE ON/OFF

 EASY HANDLING AND OPERATION FOR MOUN-TING WITHIN CABINETS OR AT WALL

Fig: Wärtsilä JOVYLINE DINrail with relay box

OPTIONS

Relay outputs via relay box

Spare battery Wärtsilä JOVYLINE DINrail 500



